


Universal Charger

GAUGES BATTERY POWER



- Indicates amount of charge in the battery

MAXIMIZES PERFORMANCE



- Helps batteries retain capacity by preventing damage from overcharge

ENSURES FULL CHARGE



- Charges batteries to 100% capacity



VERSATILE

- Charges AA, AA, C, D and 9V NiMH batteries



North America Region
[Download Instructions \(multilingual\)](#)

Product Detail:

Designation: Universal Charger

Model: CHFC2

Color: Black

Charging Capability: AA/AAA/C/D/9V

Charging Times: (estimated)	Battery (NiMH)	Capacity (mAh)	Estimated (time)
	AA	1300	2-3 hrs
	AA	2000	2-4 hrs
	AA	2300	3-6 hrs
	AAA	700-800	3 hrs
	C/D	2500	3-5 hrs
	9V	175	6 hrs

Shutoff Mechanism: Delta V Detection and Timer Control

Charging Current:
 2 or 4 "AA" 1100mA (1 battery per bay)
 1 or 2 "AA-C-D" 1100mA (1 battery per bay)
 6 or 8 "AA" 550mA (2 batteries per bay)
 3 or 4 "AA-C-D" 550mA (2 batteries per bay)
 1 to 4 "AAA" 450mA
 2 or 4 "AAA" 450mA
 6 or 8 "AAA" 450mA
 1 "9V" 30mA

Trickle Charge: "AA/C/D" 50mA
 "AAA" 25mA

Input Rating: 100-240VAC, 50/60Hz, 0.35A
 12VDC, 1A

Weight (charger): 335 grams

Dimensions (mm): 200 x 100 x 54 (H x L x W)

Safety Features: Reverse Polarity Protection
 Safety Timer to Prevent Overcharge
 Bad Battery Detection and Short Circuit Detection

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

Contents herein do not constitute a warranty.

Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with **Energizer® NiMH batteries.**