### PRODUCT DATASHEET

### NiMH Battery Charger (CHFCV)


### **Family Charger**

## North American Region Download Instructions and Warranty Information

English | Français | Español

#### **EASY**

- LED charge indicators
- Includes charge status indicators





- Charges multiple combinations of AAA, AA, C, D or 9V NiMH batteries overnight
- Charges up to 4 AA or AAA NiMH batteries at a time.



# SAFETY FEATURES

 Reverse polarity protection protects the charger and batteries against damage from incorrectly installed batteries.



# CHAR SA SAIMHB JUE 337 ATARC TOUTES LES TAILLES TOUT I PILE FOR ALL YOUR HOUSEHOLD

#### Before Using Your Charger:

Pour tous vos besoins De Batterie de Ménage

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with Energizer NiMH batteries.

### **Product Detail:**

**Designation:** Family Charger **Color:** Gun Metal Gray

Ch. .ging Capability: 2 or 4 "AA" Batteries

NOT atteries must be ch. .d in pairs according specific battery sizes.

2 or 4 "AA" Batteries
2 or 4 "C/D" Batteries
1 or 2 "9V" Batteries

Chai ing Current: "AA/AAA" 200 mA

"C/D" 200 mA "9V" 16 mA

Trickle Charge: "AA-AAA-C-D" 15-25 mA

Charging Time: (estimated)

1	Battery	Capacity	Estimated
١	(NiMH)	(mAh)	(time)
ı	AA		11.0-13.0 hrs
ı	AA	2100-2500	15.0-16.5 hrs
ı	AAA	600-800	4.5-5.0 hrs
ı	C/D	2300-2600	16.5 hrs
ı	9V	110-150	10.0-13.5 hrs

**Shutoff Mechanism**: Timer Control Max Timer Control 16.5 hours

**Weight (charger):** 500 grams (17.7 oz.) **Dimensions (mm):** 52 x 204 x 100 (H x L x W)

Safety Features: Reverse Polarity Protection

Safety Timer to Prevent Over Charge

#### **Important Notice**

This datasheet contains information specific to products manufactured at the time of its publication.

©Energizer Holdings, Inc.

Contents herein do not constitute a warranty.

